
## **Product Overview**





Manufactured exclusively for GlowbackLED, Our new MUD24V96W is a 24V 96W Dimmable LED Power Supply suitable for a wide range of LED strip and linear lighting products. Our **MUD24V96W** can be used with any phase control dimmers (Forward Phase (Triac/MLV) and Reverse Phase (ELV). Unlike our older dimmable LED power supplies our **MUD24V96W** outputs consistent, flicker-free lighting which can be **smoothly** dimmed down to 1%. Our **MUD24V96W** conveniently comes with a 3ft power cord and (US) plug for quick and easy LED strip lighting installations! This Dimmable LED Driver features an integrated wiring compartment, allowing one to make clean connections inside of the power-supply with no need for external junction boxes. The slim and compact design makes our MUD24V96W an excellent solution for under-cabinet LED lighting. Last, but certainly not least, our MUD24V96W is UL-Listed and ready for use on any commercial LED lighting project.



Wiring



## MUD24V96W

Spec Sheet

Product Code	MUD24V96W
Dimensions	8.7" L x 3.6" W x 1.6" H
Input Voltage	100-277VAC   50/60 HZ
Output Voltage	24VDC
Output Power	96W   4A
Input Power	1.3A (MAX)
Power Factor	0.95
Dimming Type	Universal Phase Dimming (TRIAC/MLV/ELV)
Dimming Range	100%-1%
Minimum Load	9.6 Watts
Warranty	5-Year Limited Warranty
Environment	Indoor/Damp Location
Listings	UL-Listed   Class-2   Type HL   RoHs   FCC

## Features

- Flicker-Free Dimming! Achieves Consistent and Smooth Light Output
- Universal Dimming! Works with any phase dimming solution. Triac/MLV/ELV!
- Suitable for use in Dry & Damp Locations
- Power Cord Attached! Plug & Play Ready out of box
- Integrated Wiring Compartment: Make Clean Connections inside of the power-supply instead of a junction box!
- Slim and Compact Design Allows for Easy Concealing!
- **UL Listed:** Approved for use on **any** Commercial Project!

## Wire Compartment



GlowbackLED® is a registered trademark of Bluegate Inc ©2020 Bluegate Inc. All Rights Reserved Specifications subject to change without notice

